



B

Technical data

- Special PVC data cables, adapted to DIN VDE 0812, 0814
- **Temperature range**
flexing -5°C to +80°C
fixed installation -30°C to +80°C
- **Nominal voltage** 250 V
- **Test voltage** 1200 V
- **Breakdown voltage** min. 2400 V
- **Insulation resistance**
min. 20 MΩhm x km
- **Capacitance** (approx.-value) at 800 Hz
core/core 0,14 mm² = 120 pF/m
core/core 0,25 mm² = 150 pF/m
- **Load** 0,14 mm² = 1,5 A
0,25 mm² = 2,5 A
- **Inductance** approx. 0,65 mH/km
- **Impedance** approx. 78 Ohm
- **K₁-coupling** approx. 300 pF/100 m
- **Minimum bending radius**
flexing 7,5x cable Ø
fixed installation 4x cable Ø
- **Radiation resistance**
up to 80x10⁶ cJ/kg (up to 80 Mrad)

Cable structure

- Bare copper, fine wire conductors, bunch stranded to DIN VDE 0295 cl. 5 and IEC 60228 cl. 5
- Special PVC core insulation YI2, to DIN VDE 0207 part 4
- Colour coded to DIN 47100
- Cores stranded in pairs with optimal lay-length
- Pairs stranded in layers with optimal lay-length
- Core wrapping with foil
- Special PVC outer sheath YM2, to DIN VDE 0207 part 5
- Sheath colour grey (RAL 7032)
- with meter marking, change-over in 2009

Properties

- Extensively oil resistant.
Chemical Resistance - see table Technical Informations
- PVC self-extinguishing and flame retardant according to VDE 0482-332-1-2, DIN EN 60332-1-2/ IEC 60332-1 (equivalent DIN VDE 0472 part 804 test method B)
- The materials used in manufacture are cadmium-free and contain no silicone and free from substances harmful to the wetting properties of lacquers

Note

- AWG sizes are approximate equivalent values. The actual cross-section is in mm².
- **screened analogue type:**
PAAR-TRONIC-CY confer page B 11

Application

These data control cables are used for flexible use with free movement without tensile stress or forced movements in dry, moist and wet rooms but not suitable for open air. PAAR-TRONIC is the perfect cable for use in areas where a small diameter is essential to complete wiring. E. g. as a control and signal cable in measuring instruments, computers, signal transfer etc. This cable is suitable only for low load application. **CE** = The product is conformed with the EC Low-Voltage Directive 2006/95/EG.

Part No.	No.pairs x cross-sec. mm ²	Outer ø ca. mm	Cop. weight kg / km	Weight ca. kg / km	AWG-No.	Part No.	No.pairs x cross-sec. mm ²	Outer ø ca. mm	Cop. weight kg / km	Weight ca. kg / km	AWG-No.
19001	1 x 2 x 0,14	3,0	2,7	20,0	26	19018	24 x 2 x 0,14	12,4	65,0	170,0	26
19002	2 x 2 x 0,14	5,0	5,4	25,0	26	19019	25 x 2 x 0,14	11,9	67,0	180,0	26
19003	3 x 2 x 0,14	5,0	8,0	31,0	26	19020	26 x 2 x 0,14	11,9	70,0	184,0	26
19004	4 x 2 x 0,14	5,4	10,7	38,0	26	19021	27 x 2 x 0,14	11,9	75,0	188,0	26
19005	5 x 2 x 0,14	6,1	13,4	45,0	26	19022	28 x 2 x 0,14	13,1	75,0	192,0	26
19006	6 x 2 x 0,14	6,6	16,1	50,0	26	19023	30 x 2 x 0,14	13,1	81,0	200,0	26
19007	7 x 2 x 0,14	6,6	18,8	57,0	26	19024	32 x 2 x 0,14	13,8	86,0	224,0	26
19008	8 x 2 x 0,14	7,6	21,5	64,0	26	19025	34 x 2 x 0,14	14,1	91,0	247,0	26
19009	10 x 2 x 0,14	8,5	26,9	78,0	26	19026	36 x 2 x 0,14	14,1	97,0	260,0	26
19010	11 x 2 x 0,14	8,6	29,5	86,0	26	19027	38 x 2 x 0,14	14,6	102,0	272,0	26
19011	12 x 2 x 0,14	8,6	32,3	94,0	26	19028	40 x 2 x 0,14	15,3	108,0	294,0	26
19012	14 x 2 x 0,14	9,3	37,6	105,0	26	19029	44 x 2 x 0,14	16,2	118,0	334,0	26
19013	15 x 2 x 0,14	9,8	40,3	108,0	26	19030	45 x 2 x 0,14	16,4	121,0	342,0	26
19014	16 x 2 x 0,14	9,8	45,0	110,0	26	19031	50 x 2 x 0,14	17,1	134,0	387,0	26
19015	18 x 2 x 0,14	10,4	48,4	119,0	26	19032	52 x 2 x 0,14	17,1	140,0	403,0	26
19016	20 x 2 x 0,14	11,1	54,0	130,0	26	19033	55 x 2 x 0,14	17,6	148,0	427,0	26
19017	22 x 2 x 0,14	12,4	59,0	150,0	26						

Dimensions and specifications may be changed without prior notice. (RB01)

Continuation ►

Part No.	No.pairs x cross-sec. mm ²	Outer ø ca. mm	Cop. weight kg / km	Weight ca. kg / km	AWG-No.
19034	1 x 2 x 0,25	3,3	5,0	32,0	24
19035	2 x 2 x 0,25	5,5	10,0	37,0	24
19036	3 x 2 x 0,25	5,8	15,0	47,0	24
19037	4 x 2 x 0,25	6,5	20,0	58,0	24
19038	5 x 2 x 0,25	7,2	25,0	70,0	24
19039	6 x 2 x 0,25	8,0	30,0	80,0	24
19040	7 x 2 x 0,25	8,0	35,0	89,0	24
19041	8 x 2 x 0,25	8,8	40,0	99,0	24
19042	10 x 2 x 0,25	10,3	50,0	114,0	24
19043	11 x 2 x 0,25	10,5	55,0	126,0	24
19044	12 x 2 x 0,25	10,5	60,0	137,0	24
19045	14 x 2 x 0,25	11,3	70,0	161,0	24
19046	15 x 2 x 0,25	11,7	75,0	174,0	24
19047	16 x 2 x 0,25	12,1	80,0	187,0	24
19048	18 x 2 x 0,25	12,8	90,0	212,0	24
19049	20 x 2 x 0,25	13,6	100,0	234,0	24
19050	22 x 2 x 0,25	14,4	110,0	250,0	24
19051	24 x 2 x 0,25	14,4	120,0	280,0	24
19052	25 x 2 x 0,25	14,8	125,0	300,0	24
19053	26 x 2 x 0,25	14,8	130,0	320,0	24
19054	27 x 2 x 0,25	14,8	135,0	330,0	24
19055	28 x 2 x 0,25	16,1	140,0	345,0	24
19056	30 x 2 x 0,25	16,1	150,0	370,0	24

Part No.	No.pairs x cross-sec. mm ²	Outer ø ca. mm	Cop. weight kg / km	Weight ca. kg / km	AWG-No.
19057	32 x 2 x 0,25	16,9	160,0	410,0	24
19058	34 x 2 x 0,25	17,5	170,0	425,0	24
19059	36 x 2 x 0,25	17,5	180,0	440,0	24
19060	38 x 2 x 0,25	18,3	190,0	480,0	24
19061	40 x 2 x 0,25	19,0	200,0	530,0	24
19062	44 x 2 x 0,25	20,0	220,0	580,0	24
19063	45 x 2 x 0,25	20,2	225,0	600,0	24
19064	50 x 2 x 0,25	21,0	250,0	650,0	24
19065	52 x 2 x 0,25	21,0	260,0	670,0	24
19066	55 x 2 x 0,25	21,7	275,0	790,0	24
19067	1 x 2 x 0,34	3,6	6,5	36,0	22
19068	2 x 2 x 0,34	6,4	13,1	42,0	22
19069	3 x 2 x 0,34	6,8	19,6	50,0	22
19070	4 x 2 x 0,34	7,3	26,1	61,0	22
19071	1 x 2 x 0,5	3,9	9,6	42,0	20
19072	2 x 2 x 0,5	7,4	19,2	51,0	20
19073	3 x 2 x 0,5	7,4	28,8	62,0	20
19074	4 x 2 x 0,5	8,3	38,4	73,0	20
19075	1 x 2 x 0,75	4,4	14,4	47,0	18
19076	2 x 2 x 0,75	7,8	28,8	59,0	18
19077	3 x 2 x 0,75	8,3	43,2	74,0	18
19078	4 x 2 x 0,75	9,0	57,6	93,0	18

Dimensions and specifications may be changed without prior notice. (RB01)

Our Service on the Internet

The screenshot shows the HELUKABEL website interface. At the top, there is a navigation menu with links for Download centre, Logistic centre, Company, Products, Quality, News, Contact, Service, Opinion, and Imprint. Below the menu, a breadcrumb trail indicates 'You are here: Home > Contact > Contact person'. A 'Contact' sidebar lists 'Headquarters Hemmingen', 'Approach', and 'Contact person'. The main content area is titled 'Contact person' and includes a search bar, a 'Post code search for Germany' field with a 'Finden Sie Ihren Ansprechpartner' button, and a 'HELUKABEL world-wide' map section.

Contact person

Enter your postal code to find out your personal customer sales consultant, who serves as your contact for questions and offers. Simply click and check it out. We are looking forward to hearing from you.

www.helukabel.de